Thyristor Modules

Liujing rectifier co., Ltd.

V_{RSM}	V_{RRM} V_{DRM}	I_{TRMS} =150A(maximum value for continous operation)		
V	V	I_{TAV} =95A(sin.180; Tc=85℃)		
900	800	SKKT 92/08E	SKKT 92B08E	SKKH 92/08E
1300	1200	SKKT 92/12E	SKKT 92B12E	SKKH 92/12E
1500	1400	SKKT 92/14E	SKKT 92B14E	SKKH 92/14E
1700	1600	SKKT 92/16E	SKKT 92B16E	SKKH 92/16E
1900	1800	SKKT 92/16E	SKKT 92B16E	SKKH 92/18E

Symbol	Conditions	Values	Units
I_{TAV}	sin. 180; Tc = 85(100)℃;	95 (68)	A
I_D	P3/180 ; Ta = 45℃; B2 / B6	70 / 85	A
	P3/180F; Ta = 35℃; B2 / B6	140 / 175	A
I_{RMS}	P3/180F; Ta = 35℃; W1 / W3	190 / 3 * 135	A
I_{TSM}	T_{vj} = 25℃; 10ms	2000	A
	T_{vj} = 125℃; 10ms	1750	A
i^2t	T_{vj} = 25℃; 8，3 ...10ms	20000	A^2S
	T_{vj} = 125℃; 8，3 ...10ms	15000	A^2S
V_T	T_{vj} = 25℃; I_T=276A	max.1.65	V
$V_{T(TO)}$	T_{vj} = 125℃	max.0.9	V
r_T	T_{vj} = 125℃	max.2	mΩ
I_{DD};I_{RD}	T_{vj} = 125℃; V_{RD}=V_{RRM} ; V_{DD}=V_{DRM}	max.20	mA
t_{gd}	T_{vj} = 25℃; I_G = 1A; di$_G$/dt = A/μs	1	μs
t_{gr}	V_D = 0.67*V_{DRM}	2	μs
$(di/dt)_{cr}$	T_{vj} = 125℃	max.150	A/μs
$(dv/dt)_{cr}$	T_{vj} = 125℃	max.1000	V/μs
t_q	T_{vj} = 125℃	250	μs
I_H	T_{vj} = 25℃ ; typ./max	150/250	mA
I_L	T_{vj} = 25℃ ; RG = 33Ω ; typ./max	300/600	mA
V_{GT}	T_{vj} = 25℃ ; d.c.	min. 3	V
I_{GT}	T_{vj} = 25℃ ; d.c.	min. 150	mA
V_{GD}	T_{vj} = 125℃ ; d.c.	max. 0.25	V
I_{GD}	T_{vj} = 125 ℃ ; d.c.	max. 6	mA
$R_{th(j-c)}$	cont.; per thyristor/per module	0.28 / 0.14	K/W
$R_{th(j-c)}$	sin. 180; per thyristor/per module	0.3 / 0.15	K/W
$R_{th(j-c)}$	rec. 120; per thyristor/per module	0.32 / 0.16	K/W
$R_{th(j-c)}$	per thyristor/per module	0.2 / 0.1	K/W
T_{vj}		- 40...+ 125	℃
T_{stg}		- 40...+ 125	℃
V_{isol}	a. c. 50Hz; r.m.s. ; 1s/1min	3600/3000	V~
M_s	to heatsink	5 ± 15%[1])	Nm
M_t	to terminal	3 ± 15%	Nm
a		5 * 9.81	m/s^2
m	approx.	95	g
Case	SKKT	LJ1	




Fig. 1L Power dissipation per thyristor vs. on-state current




Fig. 1R Power dissipation per thyristor vs. ambient temp.




Fig. 2L Power dissipation per module vs. rms current




Fig. 2R Power dissipation per module vs. case temp.




Fig. 3L Power dissipation of two modules vs. direct current




Fig. 3R Power dissipation of two modules vs. case temp.




Fig. 4L Power dissipation of three modules vs. direct and rms current




Fig. 4R Power dissipation of three modules vs. case temp.




Fig. 5 Recovered charge vs. current decrease




Fig. 6 Transient thermal impedance vs. time




Fig. 7 On-state characteristics





Fig. 8 Surge overload current vs. time






Fig. 9 Gate trigger characteristics

4006606086@B.QQ.COM

ZHEJIANG LIUJING RECTIFIER CO., LTD
Sale Departmant: Liujing Building, Yueqing City, Zhejiang Province
Add: Wanao Industrial Zone, Yueqing city, Zhejiang Province
Tel: 0086-577-62519692 0089-577-62519693
Fax: 0577-61204622
International Export: 0086-577-62571902
Technical Support: 0086-15868768965
After Service: 400-6606-086
http://www.china-liujing.com
http://www.liujingdianqi.cn
http://www.cnrectifier.com
http://www.cnthyristor.com.cn
MSN: thristors@hotmail.com

打造最具竞争力的电力半导体产品

To be the most competitive Power Semiconductor Devices manufactory.

LIUJING reserves the right to change limits, test conditions and dimensions.
윤정은 이 칼타로그 중에 데이트, 테스트 조건, 외형사이즈에 대한 최종 해석권을 가지고 있습니다.